



GOLD NOTE

Italian Music Experience

MAIN DETAILS

Frequency Response: 2Hz - 200kHz @ ± 3 dB

THD – Total Harmonic Distortion: <0.001% @ 1kHz

Gain: + 20dB – 10V

Signal to Noise ratio: - 120dB

Channel Separation: > 118dB

Volume: 0.5dB steps

Stereo/Mono mode: selectable

Absolute Phase swap: 0°/180°

Channel Left/Right swap: selectable

Booster: adjustable 3 position (by-passable on OFF)

Power supply: Dual-Mono Ultra Linear triple transformer

Analogue Input: 5 stereo XLR balanced & 5 Stereo RCA unbalanced

Digital Input (optional): TOS or Coax 24/192kHz

Input Level: 10Vrms on RCA

Input Impedance: 100k Ω

Dimensions: 430mm W x 130mm H x 375mm W

Weight: 15 Kg



P-1000

High-End Preamplifier

www.goldnote.it

info@goldnote.it

+39 0571 675005

Via della Gora, 6 | Montespertoli (Firenze) Italy 50025



HIGH-END PREAMPLIFIER

Designed for High-End systems, P-1000 is an innovative Class-A line preamplifier powered by a new proprietary Six Gain Stage design with Relays & Optical ALPS Encoder volume control and the best audio grade components to enhance the musical pleasure to a new and refined level.

P-1000 is powered by a Triple Linear Transformer power supply and features 10 independent stereo inputs: 5 fully balanced XLR and 5 RCA. Optionally a digital input is also available on demand.

The exclusive Gold Note Ultra-Balanced design featuring Six Single Gain stages provide incredible low distortion and extended linear bandwidth for true superior musicality.

FINE CONTROL & FUNCTIONS

P-1000 stores in memory the settings and the volume levels for every single audio input to allow a better experience and very quick adjustments.

It also features a large amount of functions: Mono/Stereo selection, Left/Right channel swap, Absolute Phase swap, Booster technology and fine Balance tuning.



INNOVATING THE TRADITION

P-1000 belongs to a new era of electronics where performance is combined with technology to offer the best possible musical experience: tradition and innovation meet to create a unique preamplifier with crystal clear sound.

The preamplifier it's easy to control with its large colour display showing all possible functions: it's as easy as it gets, all the settings can be found on the display allowing quick and precise fine adjustments.

A NEW SET OF FEATURES

To perfectly reproduce even old recordings, the preamplifier can be set into Mono or Stereo mode. It also allows to swap the Left & Right channels to allow the reproduction of inverted recordings as well as the absolute phase swap from 0° to 180°.

For P-1000 we developed the Booster technology: a feature that will allow you to get the best out of speakers that require robust power supplies providing greater energy in a very specific range of low frequencies (the Booster is completely bypassed when set to OFF).

P-1000 can be enhanced with the external tube output stage TUBE-1006/1012 and the inductive super power supply unit PSU-1000.